


# Asynchronní motory nakrátko

## Rozměry motorů


Typové označení motorů (objednací číslo):

Typ motoru (12. místo): **2**  
IM B14FT... (IM 3641 FT...) - s malou přírubou

menší



velikost 56-80 mm





| Velikost  | Velikost příruby | M   | N  | P   | RA | S  | T   | Z |
|-----------|------------------|-----|----|-----|----|----|-----|---|
| <b>56</b> | FT65             | 65  | 50 | 80  | -  | M5 | 2,5 | 4 |
| <b>63</b> | FT75             | 75  | 60 | 90  | 14 | M5 | 2,5 | 4 |
| <b>71</b> | FT85             | 85  | 70 | 105 | 16 | M6 | 2,5 | 4 |
| <b>80</b> | FT100            | 100 | 80 | 120 | 16 | M6 | 3   | 4 |

**3**

IM B14FT... (IM 3641 FT...) - s velkou přírubou



větší



| Velikost  | Velikost příruby | M   | N   | P   | RA | S  | T   | Z |
|-----------|------------------|-----|-----|-----|----|----|-----|---|
| <b>56</b> | FT85             | 85  | 70  | 105 | -  | M6 | 2,5 | 4 |
| <b>63</b> | FT100            | 100 | 80  | 120 | 16 | M6 | 3   | 4 |
| <b>71</b> | FT115            | 115 | 95  | 140 | 16 | M8 | 3   | 4 |
| <b>80</b> | FT130            | 130 | 110 | 160 | 16 | M8 | 3,5 | 4 |



velikost **90** - 100 mm

menší



| Velikost   | Velikost příruby | M   | N   | P   | RA | S  | T   | Z |
|------------|------------------|-----|-----|-----|----|----|-----|---|
| <b>90</b>  | FT115            | 115 | 95  | 140 | 21 | M8 | 3   | 4 |
| <b>100</b> | FT130            | 130 | 110 | 160 | 20 | M8 | 3,5 | 4 |



větší



| Velikost   | Velikost příruby | M   | N   | P   | RA | S   | T   | Z |
|------------|------------------|-----|-----|-----|----|-----|-----|---|
| <b>90</b>  | FT130            | 130 | 110 | 160 | 22 | M8  | 3,5 | 4 |
| <b>100</b> | FT165            | 165 | 130 | 200 | 20 | M10 | 3,5 | 4 |



velikost 112 - 160 mm

menší



| Velikost   | Velikost příruby | M   | N   | P   | RA | S   | T   | Z |
|------------|------------------|-----|-----|-----|----|-----|-----|---|
| <b>112</b> | FT130            | 130 | 110 | 160 | 20 | M8  | 3,5 | 4 |
| <b>132</b> | FT165            | 165 | 130 | 200 | 24 | M10 | 3,5 | 4 |
| <b>160</b> | FT215            | 215 | 180 | 250 | 16 | M12 | 4,0 | 4 |

větší



| Velikost   | Velikost příruby | M   | N   | P   | RA  | S   | T   | Z |
|------------|------------------|-----|-----|-----|-----|-----|-----|---|
| <b>112</b> | FT165            | 165 | 130 | 200 | 20  | M10 | 3,5 | 4 |
| <b>132</b> | FT215            | 215 | 180 | 250 | 16* | M12 | 4,0 | 4 |
| <b>160</b> | FT265            | 265 | 230 | 300 | 12* | M12 | 4,0 | 4 |

\* Díra v přírubě je průchozí.

FT příruba s vrtanou dírou s metrickým závitem M...  
FF příruba s průchozí vrtanou dírou