

Kaohsiung Opto-Electronics Inc.

FOR MESSRS :

DATE : Jun. 18th ,2012

# CUSTOMER'S ACCEPTANCE SPECIFICATIONS

# TX14D11VM1CPD

# Contents

No.			DACE
INO.	ITEM	SHEET No.	PAGE
1	COVER	7B64PS 2701-TX14D11VM1CPD-4	1-1/1
2	RECORD OF REVISION	7B64PS 2702-TX14D11VM1CPD-4	2-1/1
3	GENERAL DATA	7B64PS 2703-TX14D11VM1CPD-4	3-1/1
4	ABSOLUTE MAXIMUM RATINGS	7B64PS 2704-TX14D11VM1CPD-4	4-1/1
5	ELECTRICAL CHARACTERISTICS	7B64PS 2705-TX14D11VM1CPD-4	5-1/1
6	OPTICAL CHARACTERISTICS	7B64PS 2706-TX14D11VM1CPD-4	6-1/2~2/2
7	BLOCK DIAGRAME	7B64PS 2707-TX14D11VM1CPD-4	7-1/1
8	RELIABILITY TESTS	7B64PS 2708-TX14D11VM1CPD-4	8-1/1
9	LCD INTERFACE	7B64PS 2709-TX14D11VM1CPD-4	9-1/4~4/4
10	OUTLINE DIMENSIONS	7B63PS 2710-TX14D11VM1CPD-4	10-1/2~2/2
11	TOUCH PANEL	7B64PS 2711-TX14D11VM1CPD-4	11-1/2~2/2
12	APPEARANCE STANDARD	7B64PS 2712-TX14D11VM1CPD-4	12-1/4~4/4
13	PRECAUTIONS	7B64PS 2713-TX14D11VM1CPD-4	13-1/2~2/2
14	DESIGNATION OF LOT MARK	7B64PS 2714-TX14D11VM1CPD-4	14-1/1

ACCEPTED BY:\_\_\_\_\_

PROPOSED BY: Centhen

# 2. RECORD OF REVISION

DATE	SHEET No.	SUMMARY								
Nov.25,'11	7B64PS 2706-	6. OPTICAL CI	6. OPTICAL CHARACTERISTICS							
	TX14D11VM1CPD-2	Revised:								
	PAGE 6-1/2	lte	n	Symbol	Min.	Тур.	Max.			
		Color Chromaticit	Green	X	0.33	0.38	0.43			
				<u>↓</u>	1					
			Item Symbol Min. Typ. Max.							
		Color Chromaticit	Green	Х	0.28	0.33	0.38			
May 01,'12 All pages Company name changed: KAOHSIUNG HITACHI ELECTRONICS CO.,LTD. ↓ KAOHSIUNG OPTO-ELECTRONICS INC.										
	7B64PS 2704 – TX14D11VM1CPD-3 Page 4 - 1/1	4. ABSOLUTE	4. ABSOLUTE MAXIMUM RATINGS Revised : Note2							
	7B64PS 2705 – TX14D11VM1CPD-3 Page 5 - 1/1		5.1 LCD CHARACTERISTICS Added : Note3							
	7B64PS 2711 – TX14D11VM1CPD-3 Page 11 - 2/2	11.5 SAFETY / Added : Item		TIONS						
Jun. 18,'12	7B64PS-2711- TX14D11VM1CPD-4	11.2 ELECTR Changed :	I.2 ELECTRICAL CHARACTERISTICS hanged :							
	Page 11-1/2	ITEM SPECIFICATION								
		X1	-X2		210~	640Ω				
				$\downarrow$	·					
		IT	EM	COND	UCTIVE	RESIST	ANCE			
		X1	-X2		310~	950Ω				
	7B64PS-2711- TX14D11VM1CPD-4	11.4 OPTICAL Changed :	AL CHARACTERISTICS							
	Page 11-2/2		em	Specification						
			nittance	80% min.						
					,					
		1+,	em	*	Specif	ication				
			nittance		77%					
					1170					
KAOHSIUN	G OPTO-ELECTRONICS	INC. SHEET	7B64P\$	S 2702-TX14	4D11VM	1CPD-4	PAGE	2-1/ <sup>,</sup>		

# 3. GENERAL DATA

### 3.1 DISPLAY FEATURES

This module is a 5.7" QVGA of 4:3 format amorphous silicon TFT.The pixel format is vertical stripe and sub pixels are arranged as R(red), G(green), B(blue) sequentially. This display is RoHS compliant, and COG (chip on glass) technology and LED backlight are applied on this display.

Part Name	TX14D11VM1CPD
Module Dimensions	167.0(W) mm x 109.0(H) mm x (10.4)(D) mm typ.
LCD Active Area	115.2(W) mm x 86.4(H) mm
Dot Pitch	0.12(W) mm x 3(R, G, B)(W) x 0.36(H) mm
Resolution	320 x 3(RGB)(W) x 240(H) dots
Color Pixel Arrangement	R, G, B Vertical stripe
LCD Type	Transmissive Color TFT; Normally White
Display Type	Active Matrix
Number of Colors	262k Colors
Backlight	7 LEDs parallel x 3 serial (21 LEDs in total)
Weight	220g typ.
Interface	C-MOS; 18-bit RGB; 40 pins
Power Supply Voltage	3.3V for LCD; 12V for Backlight
Power Consumption	215 mW for LCD; 1.0 W for backlight
Viewing Direction	6 O'clock (without image inversion and least brightness change) 12 O'clock (contrast peak located at)
Touch Panel	Resistive type; Film on Glass; 4 wire type; Antiglare Surface.

# 4. ABSOLUTE MAXIMUM RATINGS

Item	Symbol	Min.	Max.	Unit	Remarks
Supply Voltage	VDD	-0.3	4.0	V	-
Input Voltage of Logic	VI	-0.2	VDD+0.2	V	Note 1
Operating Temperature	Тор	-20	70	°C	Note 2
Storage Temperature	Tst	-30	80	°C	Note 2

Note 1: The rating is defined for the signal voltages of the interface such as DTMG, DCLK and RGB data bus.

Note 2: The maximum rating is defined as above based on the chamber temperature, which might be different from ambient temperature after assembling the panel into the application. Moreover, some temperature-related phenomenon as below needed to be noticed:

- Background color, contrast and response time would be different in temperatures other than  $25\,^\circ\mathrm{C}\,.$ 

- Operating under high temperature will shorten LED lifetime.

KAOHSIUNG OPTO-ELECTRONICS INC.	T 7B64PS 2704-TX14D11VM1CPD-4	PAGE	4-1/1
---------------------------------	-------------------------------	------	-------

# **5. ELECTRICAL CHARACTERISTICS**

#### 5.1 LCD CHARACTERISTICS

5.1 LCD CHARACTERISTICS $T_a = 25 \ ^{\circ}C, \ \text{VSS} =$							
Item	Symbol	Condition	Min.	Тур.	Max.	Unit	Remarks
Power Supply Voltage	VDD	-	3.0	3.3	3.6	V	-
Input Voltage of Logic	N/I	"H" level	0.8VDD	-	VDD	N	Nata 4
	VI	"L" level	VSS	-	0.2VDD	V	Note 1
Power Supply Current	IDD	VDD-VSS=3.3V	-	65	-	mA	Note 2
Vsync Frequency	$f_v$	-	-	60	68	Hz	-
Hsync Frequency	$f_{H}$	-	13.1	15.2	17.7	KHz	-
DCLK Frequency	$f_{CLK}$	-	4.85	5.85	7.0	MHz	-

Note 1: The rating is defined for the signal voltages of the interface such as DTMG, DCLK and RGB data bus.

Note 2: An all black check pattern is used when measuring IDD,  $f_v$  is set to 60 Hz.

Note 3: 0.4A fuse is applied in the module for IDD. For display activation and protection purpose, power supply is recommended larger than 1.0A to start the display and break fuse once any short circuit occurred.

#### 5.2 BACKLIGHT CHARACTERISTICS

Item	Symbol	Condition	Min.	Тур.	Max.	Unit	Remarks
LED Input Voltage	VLED	Backlight Unit	11.5	12.0	12.5	V	Note1
LED Forward Current	ILED	Backlight Unit	-	84	91	mA	-
LED Lifetime	-	84 mA	-	40K	-	hrs	Note 2

 $T_a = 25 \ ^{\circ}C$ 

Note 1: Fig. 5.1 shows the LED backlight circuit. The circuit has 21 LEDs in total and R is  $255 \Omega$ .

Note 2: The estimated lifetime is specified as the time to reduce 50% brightness by applying 84 mA at 25°C.



KAOHSIUNG OPTO-ELECTRONICS INC.	SHEET NO.	7B64PS 2705-TX14D11VM1CPD-4	PAGE	5-1/1

# 6. OPTICAL CHARACTERISTICS

The optical characteristics are measured based on the conditions as below:

- Supplying the signals and voltages defined in the section of electrical characteristics.
- The backlight unit needs to be turned on for 30 minutes.
- The ambient temperature is 25  $^{\circ}\mathrm{C}\,.$

- In the dark room around 500~1000 lx, the equipment has been set for the measurements as shown in Fig 6.1.

2 217

			-		1	$T_a = 25$ °C	$f_v = 60  \text{Hz},$	VDD = 3.3V
Item Symbol Condition		Min.	Тур.	Max.	Unit	Remarks		
Brightness of	White	-		200	320	-	cd/m <sup>2</sup>	Note 1
Brightness Un	iformity	-	$\phi = 0^{\circ}, \theta = 0^{\circ},$	70	-	-	%	Note 2
Contrast Ratio	)	CR	ILED= 84 mA	120	350	-	-	Note 3
Response Tim	ne		$\phi = 0^\circ, \theta = 0^\circ$	-	45	-	ms	-
NTSC Ratio		-	$\phi = 0^\circ, \theta = 0^\circ$	-	45	-	%	-
		$\theta$ x	$\phi = 0^{\circ}, CR \ge 10$	50	60	-		
		$\theta \mathbf{x}'$	$\phi = 180^{\circ}, CR \ge 10$	50	60	-	Desmo	Nata 5
viewing Angle	Viewing Angle		$\phi = 90^{\circ}, CR \ge 10$	65	75	-	Degree	Note 5
		heta y'	$\phi = 270^{\circ}, CR \ge 10$	45	55	-		
	Dut	Х		0.55	0.60	0.65	- - - -	
	Red	Y		0.31	0.36	0.41		
	<u> </u>	Х		0.28	0.33	0.38		
Color	Green	Y	-	0.53	0.58	0.63		
Chromaticity	Dhia	Х	$\phi = 0^\circ, \theta = 0^\circ$	0.10	0.15	0.20		Note 6
	Blue	Y	]	0.03	0.08	0.13		
	White	Х	]	0.30	0.35	0.40		
	vvriite	Y		0.30	0.35	0.40		

Note 1: The brightness is measured from the center point of the panel, P5 in Fig. 6.2, for the typical value.

Note 2: The brightness uniformity is calculated by the equation as below:

Brightness uniformity =  $\frac{\text{Min. Brightness}}{\text{Max. Brightness}}$  X100%

, which is based on the brightness values of the 9 points measured by BM-5 as shown in Fig. 6.2.



Note 3: The Contrast ratio is measured from the center point of the panel, P5, and defined as the following equation:

$$CR = \frac{Brightness of White}{Brightness of Black}$$

Note 4: The definition of response time is shown in Fig. 6.3. The rising time is the period from 90% brightness to 10% brightness when the data is from white to black. Oppositely, Falling time is the period from 10% brightness rising to 90% brightness.



Note 5: The definition of viewing angle is shown in Fig. 6.4. Angle  $\phi$  is used to represent viewing directions, for instance,  $\phi = 270^{\circ}$  means 6 o'clock, and  $\phi = 0^{\circ}$  means 3 o'clock. Moreover, angle  $\theta$  is used to represent viewing angles from axis Z toward plane XY.

The viewing direction of this display is 6 o'clock, which means that a photograph with gray scale would not be reversed in color and the brightness change would be less from this direction. However, the best contrast peak would be located at 12 o'clock.





# 7. BLOCK DIAGRAM



Note 1: Signals are DCLK, Hsync, Vsync ,DE and RGB data bus.

KAOHSIUNG OPTO-ELECTRONICS INC.	SHEET NO.	7B64PS 2707-TX14D11VM1CPD-4	PAGE	7-1/1
---------------------------------	--------------	-----------------------------	------	-------

# 8. RELIABILITY TESTS

Test Item	Condition				
High Temperature	1) Operating 2) 70 °C	240 hrs			
Low Temperature	1) Operating 2) -20 °C	240 hrs			
High Temperature	1) Storage 2) 80 °C	240 hrs			
Low Temperature	1) Storage 2) -30 °C	240 hrs			
Heat Cycle	<ol> <li>1) Operating</li> <li>2) -20°C ~70°C</li> <li>3) 3hrs~1hr~3hrs</li> </ol>	240 hrs			
Thermal Shock	<ol> <li>Non-Operating</li> <li>-35 °C ↔ 85 °C</li> <li>0.5 hr ↔ 0.5 hr</li> </ol>	240 hrs			
High Temperature & Humidity	<ol> <li>1) Operating</li> <li>2) 40 °C &amp; 85%RH</li> <li>3) Without condensation</li> <li>(Note3)</li> </ol>	240 hrs			
Vibration	<ol> <li>Non-Operating</li> <li>2) 20~200 Hz</li> <li>3) 2G</li> <li>4) X, Y, and Z directions</li> </ol>	1 hr for each direction			
Mechanical Shock	1) Non-Operating 2) 10 ms 3) 50G 4) $\pm X, \pm Y$ and $\pm Z$ directions	Once for each direction			
ESD	1) Operating 2) Tip: 200 pF, 250 $\Omega$ 3) Air discharge for glass: ± 8KV 4) Contact discharge for metal frame: ± 8KV	1) Glass: 9 points 2) Metal frame: 8 points (Note4)			

Note 1: Display functionalities are inspected under the conditions defined in the specification after the reliability tests.

- Note 2: The display is not guaranteed for use in corrosive gas environments.
- Note 3: Under the condition of high temperature & humidity, if the temperature is higher than 40°C, the humidity needs to be reduced as Fig. 8.1 shown.
- Note 4: All pins of LCD interface (CN1) have been tested by ±100V contact discharge of ESD under non-operating condition.



# 9. LCD INTERFACE

# 9.1 INTERFACE PIN CONNECTIONS

The display interface connector is FA5B040HP1R3000 made by JAE (Thickness:  $0.3 \pm 0.05$ mm; Pitch:  $0.5 \pm 0.05$ mm) and more details of the connector are shown in the section of outline dimension.

Pin assignment of LCD interface is as below:

Pin No.	Signal	Function	Pin No.	Signal	Function
1	VDD		21	G4	Green Date
2	VDD	Dever Supply for Logic	22	G3	Green Data
3	VDD	Power Supply for Logic	23	VSS	GND
4	VDD		24	G2	
5	NC	No Connection	25	G1	Green Data
6	DTMG	Timing Signal for Data	26	G0	
7	VSS	GND	27	VSS	GND
8	DCLK	Dot Clock	28	R5	
9	VSS	GND	29	R4	Red Data
10	NC	No Connection	30	R3	
11	VSS	GND	31	VSS	GND
12	B5		32	R2	
13	B4	Blue Data	33	R1	Red Data
14	B3		34	R0	
15	VSS	GND	35	(IC)	Note 1
16	B2		36	VSS	GND
17	B1	Blue Data	37	NC	
18	B0		38	NC	No Connection
19	VSS	GND	39	NC	No Connection
20	G5	Green Data	40	NC	

Note 1: Keep open electrically , KOE test use only.

The backlight interface connector is BHR-03VS-1 made by JST, and pin assignment of backlight is as below:

Pin No.	Signal	Level	Function
1	$V_{LED}$ +	-	Power Supply for LED
2	NC	-	No connection
3	V <sub>LED</sub> -	-	GND

#### 9.2 TIMING CHART

DTMG (Data Enable) is the signal to determine valid data, and the timing of DTMG can be determined from Hsync and Vsync as below. For this display, only DTMG and DCLK are the essential signals. Hsync and Vsync are not necessary to connect to display interface after DTMG has been generated and input.



	Item	Symbol	Min.	Тур.	Max.	Unit	
	Cycle time	t <sub>CLK</sub>	142	171	206		
	Low level Width	t <sub>WCL</sub>	12	-	-		
	High level Width	t <sub>WCH</sub>	12	-	-	ns	
DCLK	Rise time	t <sub>rCLK</sub>	-	-	25		
	Fall time	t <sub>fCLK</sub>	-	-	25		
	Duty	D	0.45	0.5	0.55	-	
	Set up time	t <sub>SH</sub>	5	-	-		
	Hold time	t <sub>HH</sub>	10	-	-	ns	
Hsync	Cycle	t <sub>HP</sub>	370	385	397	10111	
	Valid width	t <sub>WH</sub>	4	5	-	tCLK	
	Rise/Fall time	t <sub>Hr</sub> ,t <sub>Hf</sub>	-	-	30	ns	
	Set up	t <sub>SV</sub>	0	-	-	1.0	
	Hold	t <sub>HV</sub>	2	-	-	tCLK	
Vsync	Cycle	t <sub>VP</sub>	251	253	261	4	
	Valid width	t <sub>WV</sub>	2	2	-	tHP	
	Rise/Fall time	t <sub>∨r</sub> ,t <sub>∨f</sub>	-	-	50	ns	
	Set up time	t <sub>SI</sub>	5	-	-		
	Hold time	t <sub>HI</sub>	10	-	-	ns	
	Rise/Fall time	t <sub>Ir</sub> ,t <sub>If</sub>	-	-	30	ns	
DTMG	Horizontal back porch	t <sub>HBP</sub>	28	35	-	1.0	
	Horizontal front porch	t <sub>HFP</sub>	22	30	-	tCLK	
	Vertical back porch	t <sub>VBP</sub>	6	7	-	4	
	Vertical front porch	t <sub>VFP</sub>	5	6	-	tHP	
	Set up time	t <sub>SD</sub>	5	-	-		
Data	Hold time	t <sub>HD</sub>	10	-	-	ns	
	Rise/Fall time	t <sub>Dr</sub> ,t <sub>Df</sub>	-	-	25	ns	

## 9.3 INTERFACE TIMING SPECIFICATIONS

Note 1: Vsync needs to be set as odd numbers.

#### 9.4 POWER SEQUENCE



Fig. 9.1

- Note 1: In order to avoid any damages, the correct power On sequence must be followed and VDD have to be applied before all other signals (DTMG, DCLK, RGB data). The opposite is true for power Off where VDD have to be remained on until all other signals have been switch off. The recommended time period is 1 second.
- Note 2: In order to avoid showing uncompleted patterns in transient state. It is recommended that switching the backlight on is delayed for 1 second after the signals have been applied. The opposite is true for power Off where the backlight have to be switched off 1 second before the signals are removed.

	COLOR &		Data Signal																
	Gray Scale	R5	R4	R3	R2	R1	R0	G5	G4	G3	G2	G1	G0	B5	B4	B3	B2	B1	B0
	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red (0)	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0
	Green (0)	0	0	0	0	0	0	1	1	1	1	1	1	0	0	0	0	0	0
Basic	Blue (0)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1
Color	Cyan	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1
	Magenta	1	1	1	1	1	1	0	0	0	0	0	0	1	1	1	1	1	1
	Yellow	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0
	White	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red (62)	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0
	Red (61)	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0
Red	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	•	:	:	:	:	:	:	:	:		:	:	:	:	:
	Red (1)	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red (0)	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0
	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green (62)	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0
	Green (61)	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0
Green	: ,	:	:	:	:		:	:	:	:	:		:	:	:	:	:		:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	Green (1)	0	0	0	0	0	0	1	1	1	1	1	0	0	0	0	0	0	0
	Green (0)	0	0	0	0	0	0	1	1	1	1	1	1	0	0	0	0	0	0
	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Blue (62)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
	Blue (61)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0
Blue	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	Blue (1)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	0
	Blue (0)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1
			-											-	-				
OHSIUN	G OPTO-ELEC	TRC	NIC	S INC	;.   5	SHEE NO		7	'B64I	PS 27	709-T	X14	D11V	M1C	PD-4	ļ	PA	GE	9-4

#### 9.5 DATA INPUT for DISPLAY COLOR







Scale : NTS

Unit : mm

# 11. TOUCH PANEL

The type of touch panel used on this display is resistive, analog, 4-wire and film on glass, and more characteristics are shown as below:

### **11.1 OPERATING CONDITIONS**

Item	Specification	Remarks
Operating Voltage	5VDC max.	-

### **11.2 ELECTRICAL CHARACTERISTICS**

Item		Specification	Remarks
Resistance	Resistance X1-X2		
Between Terminal Y1-Y2		<b>240~680</b> Ω	-
Insulation Resistance	X-Y	<b>20M</b> $\Omega$ min.	At 25V DC
	Х	±1.5% max.	
Linearity	Y	±1.5% max.	Note 1
Chattering		10ms max.	-

Note 1: The test conditions and equipments of linearity are as below:

- Material of pen: poly-acetal resin
- End shape: R 0.8 mm
- Test force: 150 gf
- Pitch: 10 mm
- Test area is shown in Fig. 11.1



As shown in Fig. 11.2, applying voltage meter to measure Va, Vb and Vxm, where Va is the maximum voltage in the active area; Vb is the minimum voltage in the active area; Vxm is the measured voltage of point x selected by random. Afterwards, the linearity can be calculated by following equation:

$$Linearity = \frac{|Vxi - Vxm|}{Va - Vb} \times 100\%,$$

where Vxi is the idea voltage of point x.

The method to measure the linearity of Y-axis is the same as above.

### **11.3 MECHANICAL CHARACTERISTICS**

Item	Specification	Remarks
Pen Input Pressure	1.2N max.	R0.8, Polyacetal Pen
Finger	1.2N max.	R8.0, Silicon Rubber
Surface Hardness	2H min.	JIS K 5400

#### **11.4 OPTICAL CHARACTERISTICS**

Item	Specification	Remarks
Transmittance	77% min.	-

#### **11.5 SAFETY AND ATTENTIONS**

- 1) Do not put heavy shock or stress on the touch panel.
- 2) Please use soft cloth or absorbent cotton with ethanol to clean the touch panel by gently wiping. Moreover, please wipe it by horizontal or vertical direction instead of circling to prevent leaving scars on the touch panel's surface.
- 3) Do not use any harmful chemicals such as acetone, toluene, and isopropyl alcohol to clean the display's surface.
- 4) UV protection is recommended to avoid the possibility of performance degrading when touch panel is likely applied under UV environment for a long period of time.

KAOHSIUNG OPTO-ELECTRONICS INC.	SHEET NO.	7B64PS 2711-TX14D11VM1CPD-4	PAGE	11-2/2
---------------------------------	--------------	-----------------------------	------	--------

# **12. APPEARANCE STANDARD**

The appearance inspection is performed in a dark room around 500~1000 lx based on the conditions as below:

- The distance between inspector's eyes and display is 30 cm.
- The viewing zone is defined with angle  $\theta$  shown in Fig. 12.1 The inspection should be performed within 45° when display is shut down. The inspection should be performed within 5° when display is power on.



Fig 12.1

#### 12.1 THE DEFINITION OF LCD ZONE

LCD panel is divided into 3 areas as shown in Fig.12.2 for appearance specification in next section. A zone is the LCD active area (dot area); B zone is the area, which extended 1 mm out from LCD active area; C zone is the area between B zone and metal frame.

In terms of housing design, B zone is the recommended window area customers' housing should be located in.



Fig 12.2

### **12.2 LCD APPEARANCE SPECIFICATION**

The specification as below is defined as the amount of unexpected phenomenon or material in different zones of LCD panel. The definitions of length, width and average diameter using in the table are shown in Fig. 12.3 and Fig. 12.4.

	Criteria							one
	Length (mm)	Width	ı (mm)	Maximum nu	umber	Minimum space		
	Ignored	ed W≦0.02		Ignored		-		
	L≦40	0.02 <w< td=""><td>/≦0.04</td><td>10</td><td></td><td>-</td><td></td><td></td></w<>	/≦0.04	10		-		
	L≦20	N	/≦0.04	10		-		
Scratches		A,B						
	Average diamet	er (mm)	Maxim	um number	Mir	nimum space		
	D≦0.2		I	gnore		-		
	D≦0.4			10		-		
Dent		S	Serious one is not allowed					
Wrinkles in polarizer		S	erious on	e is not allowed	b		А	
	Average di	ameter (r	nm)	Мах	kimum r	number		
		D≦0.2			Ignore	ed		
Bubbles on polarizer	0.2<	D≦0.3			12		А	
	0.3<	D≦0.5			3			
	0.5 <i< td=""><td>D</td><td></td><td></td><td>none</td><td>9</td><td></td><td>_</td></i<>	D			none	9		_
		Fi	lamentou	s (Line shape	e)			
	Length (mm)		Width (mm)		Maximum number			
	L≦2.0		W≦0.03		Ignored		A,B	
	L≦3.0		0.03<	W≦0.05	6			
	L≦2.5		0.05<	W≦0.1		1		
			Round	(Dot shape)				
1) Stains	Average diame	eter	Movimu	m numbor	Minimum Space			
<ol> <li>2) Foreign Materials</li> <li>3) Dark Spot</li> </ol>	(mm)		Maximum number		IVIII	imum space		
S) Dark Spor	D<0.2	2	Ignored			-		
	0.2≦D≦0.3	3	10		10mm		A,B	
	0.3≦D>0.4	4	5			30mm		
	0.4≦D		none			-		
	In total		Filamentous + Round=10					
	Those wiped out easily are acceptable							
			Т	уре	Max	imum number		
				dot		4		
			2 adja	cent dot		1		
	Bright dot-def	ect 3	adjacent	dot or above	١	lot allowed		
			De	ensity		2/ø 20mm		
Dot-Defect				total		5	А	
(Note 1)				dot		5	/ `	
				cent dot		2		
	Dark dot-defe	ect 3		dot or above		lot allowed		
				ensity		3/ø 20mm		
			In total		5			
		In to	tal			10		



Fig 12.3

Fig 12.4

Note 1: The definitions of dot defect are as below:

- The defect area of the dot must be bigger than half of a dot.
- For bright dot-defect, showing black pattern, the dot's brightness must be over 30% brighter than others.
- For dark dot-defect, showing white pattern, the dot's brightness must be under 70% darker than others.
- The definition of 1-dot-defect is the defect-dot, which is isolated and no adjacent defect-dot.
- The definition of adjacent dot is shown as Fig. 12.5.
- The Density of dot defect is defined in the area within diameter  $\phi$  =20mm.



The dots colored gray are adjacent to defect-dot A.

Fig 11.5

### 12.3 TOUCH PANEL APPEARANCE SPECIFICATION

The specification as below is defined by the amount of unexpected material in different zones of touch panel.

Item		Applied zone					
	Width (mm)	Length (mm)		Maximum number			
Scratches	W>0.1	L≧	10	Not allowed			
Scratches	0.10≧W>0.05	L<	10	4 pcs max.	A,B		
	0.05≧W	L<	10	Ignored			
	Fi	lamentous	(Line shap	e)			
	Width (mm)		n (mm)	Maximum number			
	0.10≧W>0.05	3 <l< td=""><td>Not allowed</td><td>A,B</td></l<>		Not allowed	A,B		
Foreign Motoriolo	0.05≧W	L≦	≦3	Ignored			
Foreign Materials		Round (Dot shape)					
	Average diameter	' (mm)	Ma	A,B			
	D>0.3	35		Not allowed			
	0.35≧D>0.2	35≧D>0.25		6 pcs max.	В		
	D≦0.25			A,B			

The limitation of glass flaw occurred on touch panel is defined in the table as below.

Item	Specific	ations
Edge flaw	X Y	$X \le 5.0 \text{ mm}$ $Y \le 3.0 \text{ mm}$ $Z \le \text{Thickness}$
Corner flaw	X	$X \le 3.0 \text{ mm}$ $Y \le 3.0 \text{ mm}$ $Z \le \text{Thickness}$
Progressive flaw		Not allowed

KAOHSIUNG OPTO-ELECTRONICS INC.	SHEET NO.	7B64PS 2712-TX14D11VM1CPD-4	PAGE	12-4/4
---------------------------------	--------------	-----------------------------	------	--------

# **13. PRECAUTIONS**

### **13.1 PRECAUTIONS of MOUNTING**

- 1) Please refer to Fig. 13.1 for housing the display with touch panel into applications. The Fig. 13.1 shows some points as below:
- The cushion needs to be designed between housing and touch panel in order to avoid unexpected pressure to cause any wrong reactions, and the cushion should be located in the insulated area.
- The housing should not cover the active area of touch panel as the figure shown.



Fig 13.1

#### 13.2 PRECAUTIONS of ESD

- 1) Before handling the display, please ensure your body has been connected to ground to avoid any damages by ESD. Also, do not touch display's interface directly when assembling.
- 2) Please remove the protection film very slowly before turning on the display to avoid generating ESD.

#### **13.3 PRECAUTIONS of HANDLING**

- 1) In order to keep the appearance of display in good condition, please do not rub any surfaces of the displays by sharp tools harder than 3H, especially touch panel, metal frame and polarizer.
- 2) Please do not stack the displays as this may damage the surface. In order to avoid any injuries, please avoid touching the edge of the glass or metal frame and wore gloves during handling.
- 3) Touching the polarizer or terminal pins with bare hand should be avoided to prevent staining and poor electrical contact.
- 4) Do not use any harmful chemicals such as acetone, toluene, and isopropyl alcohol to clean display's surfaces.
- 5) Please use soft cloth or absorbent cotton with ethanol to clean the display by gently wiping. Moreover, when wiping the display, please wipe it by horizontal or vertical direction instead of circling to prevent leaving scars on the display's surface, especially polarizer.
- 6) Please wipe any unknown liquids immediately such as saliva, water or dew on the display to avoid color fading or any permanently damages.

NO.

7) Maximum pressure to the surface of the display must be less than  $1.96 \times 10^4$  Pa. If the area of adding pressure is less than  $1 \text{ cm}^2$ , the maximum pressure must be less than  $1.96 \times 10^4$  Pa.

#### **13.4 PRECAUTIONS OF OPERATING**

- Please input signals and voltages to the displays according to the values defined in the section of electrical characteristics to obtain the best performance. Any voltages over than absolute maximum rating will cause permanent damages to this display. Also, any timing of the signals out of this specification would cause unexpected performance.
- 2) When the display is operating at significant low temperature, the response time will be slower than it at 25 C°. In high temperature, the color will be slightly dark and blue compared to original pattern. However, these are temperature-related phenomenon of LCD and it will not cause permanent damages to the display when used within the operating temperature.
- 3) The use of screen saver or sleep mode is recommended when static images are likely for long periods of time. This is to avoid the possibility of image sticking.
- 4) Spike noise can cause malfunction of the circuit. The recommended limitation of spike noise is no bigger than  $\pm 100$  mV.

#### 13.5 PRECAUTIONS of STORAGE

If the displays are going to be stored for years, please be aware the following notices.

- 1) Please store the displays in a dark room to avoid any damages from sunlight and other sources of UV light.
- 2) The recommended long term storage temperature is between 10 C° ~35 C° and 55%~75% humidity to avoid causing bubbles between polarizer and LCD glasses, and polarizer peeling from LCD glasses.
- 3) It would be better to keep the displays in the container, which is shipped from KOE, and do not unpack it.
- 4) Please do not stick any labels on the display surface for a long time, especially on the polarizer.

# 14. DESIGNATION of LOT MARK

1) The lot mark is showing in Fig.13.3. First 4 digits are used to represent production lot, T represented made in Taiwan, and the last 5 digits are the serial number.



2) The tables as below are showing what the first 4 digits of lot mark are shorted for.

Mark
2
3
4
5
6

Month	Mark	Month	Mark
1	01	7	07
2	02	8	08
3	03	9	09
4	04	10	10
5	05	11	11
6	06	12	12

Week (Days)	Mark
1~7	1
8~14	2
15~21	3
22~28	4
29~31	5

3) Except letters I and O, revision number will be shown on lot mark and following letters A to Z.

4) The location of the lot mark is on the back of the display shown in Fig. 14.1.



Fig 14.1

KAOHSIUNG OPTO-ELECTRONICS INC.	SHEET NO.	7B64PS 2714-TX14D11VM1CPD-4	PAGE	14-1/1
---------------------------------	--------------	-----------------------------	------	--------